

LCD-80

Liquid Crystal Display



Intelligent/Addressable Devices

General

The LCD-80 is an 80-character, backlit LCD display annunciator for the NOTIFIER AFP-2800 and AFP-2802 fire indicator panels (FIP). Up to 32 LCD-80s may be connected onto the two-wire distributed ring. The LCD-80 has two basic modes of operation, "Terminal" and "Annunciator" mode.

Common Features

- 80-character backlit Liquid Crystal Display (20 characters x 4 lines).
- Time and date display field.
- Can be remotely located up to 1000 metres from the control panel.
- Mutable local piezo sounder with alarm/fault/isolate resound.
- Flush or surface mount options available.
- EIA-485 interface: up to 32 per FIP.

Terminal Mode

In "Terminal" mode, the LCD-80 mimics the AFP-2800 and AFP-2802 displays.

- No programming necessary.
- LCD-80 displays time, date, and events received from the panel.
- Displays device type identifiers.
- Alarm/fault/isolate count.
- Individual buttons to display Alarms, Faults or Isolates.
- Scroll buttons to view multiple events.
- Mute button to silence internal sounder.



Annunciator Mode

When operated in "Annunciator" mode, the LCD-80 is an alphanumeric display module that acts as a remote display interface to the AFP-2800 or AFP-2802 FIP. It displays pre-programmed messages which are activated by a script event in the FIP.

- Up to 64 pre-programmable messages of 60 characters each, programmed via AFP-2800 PCI.
- Displays message number read, against total number of active messages.
- Scroll buttons to view multiple messages.

Specifications

External Supply Voltage:	20VDC to 28VDC
Standby Current:	100mA
Alarm Current:	100mA
Communications Link:	EIA485 multi-dropped

Ordering Information

10198	LCD-80/2800 80 character LCD remote mimic
-------	---

© 2009 by Honeywell International Inc. All rights reserved.
Unauthorised use of this document is strictly prohibited.

This document is not intended for installation purposes.
We try to keep our product information up-to-date and accurate.
We cannot cover all specific applications or anticipate all requirements.
All specifications are subject to change without notice.

For more information contact your nearest Notifier Sales Office or Distributor
www.notifier.com.au
